

CLASSE

Sigma SSP Infrared Codes

The Classé Sigma SSP uses RC6 protocol for infrared communications. The following list of infrared codes can be used to program a universal or learning remote control. The Classé Remote Control uses a frequency of 56.0 kHz. Please refer to your remote control's user manual for information on how to program your remote control.

| Sys code | IR code | Action |
|----------|---------|-----------------------------------|
| 116 | 2 | Change input to input 1 |
| 116 | 3 | Change input to input 2 |
| 116 | 4 | Change input to input 3 |
| 116 | 5 | Change input to input 4 |
| 116 | 6 | Change input to input 5 |
| 116 | 7 | Change input to input 6 |
| 116 | 8 | Change input to input 7 |
| 116 | 9 | Change input to input 8 |
| 116 | 10 | Go to next input |
| 116 | 11 | Go to previous input |
| 116 | 12 | Toggle Standby/Operate |
| 200 | 13 | Toggle Mute/Unmute |
| 116 | 14 | Info (go to status screen) |
| 116 | 15 | Cycle through display intensities |
| 200 | 16 | Volume up |
| 200 | 17 | Volume down |
| 116 | 18 | Tone |
| 116 | 19 | Late Night Toggle |
| 116 | 21 | Balance (go to balance screen) |
| 200 | 56 | Function key F1 |
| 200 | 57 | Function key F2 |
| 116 | 68 | DSP Mode Up |
| 116 | 84 | Menu |
| 116 | 85 | Home |
| 116 | 88 | Step up (navigate up, +) |
| 116 | 89 | Step down (navigate down, -) |
| 116 | 90 | Step left (navigate left) |
| 116 | 91 | Step right (navigate right) |
| 116 | 92 | Enter |
| 116 | 120 | Change input to input 9 |
| 116 | 121 | Change input to input 10 |
| 116 | 122 | Change input to input 11 |
| 116 | 123 | Change input to input 12 |

| Sys code | IR code | Action |
|----------|---------|-------------------------------------|
| 116 | 124 | Change input to input 13 |
| 116 | 125 | Change input to input 14 |
| 116 | 126 | Change input to input 15 |
| 116 | 127 | Change input to input 16 |
| 116 | 128 | Change input to input 17 |
| 116 | 129 | Change input to input 18 |
| 200 | 134 | Function key F3 |
| 200 | 135 | Function key F4 |
| 200 | 136 | Function key F5 |
| 200 | 137 | Function key F6 |
| 200 | 138 | Function key F7 |
| 200 | 139 | Function key F8 |
| 116 | 150 | Set unit to Operate (Turn unit on) |
| 116 | 151 | Set unit to Standby (Turn unit off) |
| 200 | 152 | Set Mute mode on (Mute) |
| 200 | 153 | Set Mute mode off (Unmute) |
| 116 | 160 | Late Night On |
| 116 | 161 | Late Night Off |
| 116 | 167 | DSP Mode Down |
| 116 | 185 | Configuration 1 |
| 116 | 186 | Configuration 2 |
| 116 | 187 | Configuration 3 |
| 116 | 188 | Configuration 4 |
| 116 | 189 | Configuration 5 |
| 116 | 190 | Configuration 6 |
| 116 | 206 | Go to next Configuration |
| 116 | 207 | Go to previous Configuration |
| 116 | 216 | Dolby Volume Toggle |
| 116 | 217 | Access Lipsync menu page |
| 116 | 220 | Mode01: Mono |
| 116 | 221 | Mode02: Stereo |
| 116 | 222 | Mode03: Party |
| 116 | 223 | Mode04: Mono Plus |
| 116 | 224 | Mode05: Movie Plus |
| 116 | 225 | Mode06: Music Plus |
| 116 | 226 | Mode07: PLII |
| 116 | 227 | Mode08: PLIIz Music |
| 116 | 228 | Mode09: PLIIz Movie |
| 116 | 229 | Mode10: PLIIz Matrix |
| 116 | 230 | Mode11: PLIIz Game |
| 116 | 231 | Mode12: DTS Neo6 |
| 116 | 232 | Mode13: DTS Neo6 Music |
| 116 | 233 | Mode14: DTS Neo6 Cinema |
| 116 | 234 | Mode15: Discrete |

| Sys code | IR code | Action |
|----------|---------|----------------------------|
| 116 | 235 | Mode16: Dolby EX |
| 116 | 236 | Mode17: DTS Neo6 Music ES |
| 116 | 237 | Mode18: DTS Neo6 Cinema ES |
| 116 | 247 | Go to EQ Menu |

SIGMA SSP HEX CODES

RC6 MODE 0, SYSTEM CODE 116

| IR CODE 2 TOGGLE 0 | INPUT 1 |
|---|---------|
| 0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 125C | |
| IR CODE 2 TOGGLE 1 | INPUT 1 |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 125C | |
| IR CODE 3 TOGGLE 0 | INPUT 2 |
| 0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 1275 | |
| IR CODE 3 TOGGLE 1 | INPUT 2 |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 1275 | |
| IR CODE 4 TOGGLE 0 | INPUT 3 |
| 0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 125C | |
| IR CODE 4 TOGGLE 1 | INPUT 3 |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 125C | |
| IR CODE 5 TOGGLE 0 | INPUT 4 |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0032 1275 | |
| IR CODE 5 TOGGLE 1 | INPUT 4 |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0032 1275 | |

SIGMA SSP HEX CODES

| IR CODE 6 TOGGLE 0 | INPUT 5 |
|--|------------|
| 0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0032 0019 125C | |
| IR CODE 6 TOGGLE 1 | INPUT 5 |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0032 0019 125C | |
| IR CODE 7 TOGGLE 0 | INPUT 6 |
| 0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 1275 | |
| IR CODE 7 TOGGLE 1 | INPUT 6 |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 1275 | |
| IR CODE 8 TOGGLE 0 | INPUT 7 |
| 0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 125C | |
| IR CODE 8 TOGGLE 1 | INPUT 7 |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 125C | |
| IR CODE 9 TOGGLE 0 | INPUT 8 |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0032 1275 | |
| IR CODE 9 TOGGLE 1 | INPUT 8 |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0032 1275 | |
| IR CODE 10 TOGGLE 0 | NEXT INPUT |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0032 0031 0019 125C | |

SIGMA SSP HEX CODES

| IR CODE 10 TOGGLE 1 | NEXT INPUT |
|--|--------------------------|
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0032 0031 0019 125C | |
| IR CODE 11 TOGGLE 0 | PREVIOUS INPUT |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0032 0019 0019 1275 | |
| IR CODE 11 TOGGLE 1 | PREVIOUS INPUT |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0032 0019 0019 1275 | |
| IR CODE 12 TOGGLE 0 | STANDBY/OPERATE |
| 0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0032 0019 0019 125C | |
| IR CODE 12 TOGGLE 1 | STANDBY/OPERATE |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0032 0019 0019 125C | |
| IR CODE 14 TOGGLE 0 | INFO |
| 0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0032 0019 0019 125C | |
| IR CODE 14 TOGGLE 1 | INFO |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0032 0019 0019 125C | |
| IR CODE 15 TOGGLE 0 | TOGGLE DISPLAY INTENSITY |
| 0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0032 0019 0019 1275 | |
| IR CODE 15 TOGGLE 1 | TOGGLE DISPLAY INTENSITY |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0032 0019 0019 1275 | |

SIGMA SSP HEX CODES

| IR CODE 18 TOGGLE 0 | tone |
|---|-------------------|
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0032 0031 0019 125C | |
| IR CODE 18 TOGGLE 1 | tone |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0032 0031 0019 125C | |
| IR CODE 19 TOGGLE 0 | LATE NIGHT TOGGLE |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0032 0031 0019 0019 0032 0019 1275 | |
| IR CODE 19 TOGGLE 1 | LATE NIGHT TOGGLE |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0032 0019 0019 1275 | |
| IR CODE 21 TOGGLE 0 | BALANCE |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0032 0031 0032 0031 0032 1275 | |
| IR CODE 21 TOGGLE 1 | BALANCE |
| 0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0019 0019 0019 0032 0031 0032 0031 0032 1275 | |
| IR CODE 68 TOGGLE 0 | NEXT DSP MODE |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 125C | |
| IR CODE 68 TOGGLE 1 | NEXT DSP MODE |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 125C | |
| IR CODE 84 TOGGLE 0 | MENU |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0031 0032 0031 0032 0031 0019 0019 0019 125C | |

SIGMA SSP HEX CODES

| IR CODE 84 TOGGLE 1 | MENU |
|---|-------------|
| 0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0031 0032 0031 0032 0031 0019 0019 0019 125C | |
| IR CODE 85 TOGGLE 0 | HOME |
| 0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0031 0032 0031 0032 0031 0032 1275 | |
| IR CODE 85 TOGGLE 1 | HOME |
| 0000 004A 0000 000F 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0031 0032 0031 0032 0031 0032 1275 | |
| IR CODE 88 TOGGLE 0 | CURSOR UP |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0031 0032 0019 0019 0032 0019 0019 0019 125C | |
| IR CODE 88 TOGGLE 1 | CURSOR UP |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0031 0032 0019 0019 0032 0019 0019 0019 125C | |
| IR CODE 89 TOGGLE 0 | CURSOR DOWN |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0031 0032 0019 0019 0032 0019 0019 0032 1275 | |
| IR CODE 89 TOGGLE 1 | CURSOR DOWN |
| 0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0031 0032 0019 0019 0032 0019 0019 0032 1275 | |
| IR CODE 90 TOGGLE 0 | CURSOR LEFT |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0031 0032 0019 0019 0032 0032 0031 0019 125C | |
| IR CODE 90 TOGGLE 1 | CURSOR LEFT |
| 0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0031 0032 0019 0019 0032 0032 0031 0019 125C | |

SIGMA SSP HEX CODES

| IR CODE 91 TOGGLE 0 | CURSOR RIGHT |
|--|--------------|
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0031 0032 0019 0019 0032 0032 0019 0019 1275 | |
| IR CODE 91 TOGGLE 1 | CURSOR RIGHT |
| 0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0031 0032 0019 0019 0032 0032 0019 0019 1275 | |
| IR CODE 92 TOGGLE 0 | ENTER |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0031 0032 0019 0019 0019 0019 0032 0019 0019 125C | |
| IR CODE 92 TOGGLE 1 | ENTER |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0031 0032 0019 0019 0019 0019 0032 0019 0019 125C | |
| IR CODE 120 TOGGLE 0 | INPUT 9 |
| 0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 125C | |
| IR CODE 120 TOGGLE 1 | INPUT 9 |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0032 0019 0019 125C | |
| IR CODE 121 TOGGLE 0 | INPUT 10 |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0032 0019 0019 0032 0019 1275 | |
| IR CODE 121 TOGGLE 1 | INPUT 10 |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0032 0019 0019 0032 0019 1275 | |
| IR CODE 122 TOGGLE 0 | INPUT 11 |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0032 0019 0019 0032 0031 0019 125C | |

SIGMA SSP HEX CODES

| IR CODE 122 TOGGLE 1 | INPUT 11 |
|---|----------|
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 0032 0032 0031 0019 125C | |
| IR CODE 123 TOGGLE 0 | INPUT 12 |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 0019 0032 0032 0019 0019 1275 | |
| IR CODE 123 TOGGLE 1 | INPUT 12 |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 0032 0032 0019 0019 1275 | |
| IR CODE 124 TOGGLE 0 | INPUT 13 |
| 0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 125C | |
| IR CODE 124 TOGGLE 1 | INPUT 13 |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 125C | |
| IR CODE 125 TOGGLE 0 | INPUT 14 |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0032 1275 | |
| IR CODE 125 TOGGLE 1 | INPUT 14 |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 0019 0019 0032 0032 0019 0019 1275 | |
| IR CODE 126 TOGGLE 0 | INPUT 15 |
| 0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 125C | |
| IR CODE 126 TOGGLE 1 | INPUT 15 |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 125C | |

SIGMA SSP HEX CODES

| IR CODE 127 TOGGLE 0 | INPUT 16 |
|--|----------|
| 0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 0019 0019 1275 | |
| IR CODE 127 TOGGLE 1 | INPUT 16 |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0032 0032 0031 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 0019 0019 0019 1275 | |
| IR CODE 128 TOGGLE 0 | INPUT 17 |
| 0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 125C | |
| IR CODE 128 TOGGLE 1 | INPUT 17 |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 125C | |
| IR CODE 129 TOGGLE 0 | INPUT 18 |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 1275 | |
| IR CODE 129 TOGGLE 1 | INPUT 18 |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 1275 | |
| IR CODE 150 TOGGLE 0 | OPERATE |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0019 0019 0032 0031 0032 0019 0019 0032 0019 125C | |
| IR CODE 150 TOGGLE 1 | OPERATE |
| 0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0019 0019 0032 0019 125C | |
| IR CODE 151 TOGGLE 0 | STANDBY |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0019 0019 0032 0031 0032 0019 0019 0019 0019 1275 | |

SIGMA SSP HEX CODES

| IR CODE 151 TOGGLE 1 | STANDBY |
|---|---------------------|
| 0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0019 0019 0032 0031 0032 0019 0019 0019 0019 1275 | |
| IR CODE 160 TOGGLE 0 | LATE NIGHT MODE ON |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0019 125C | |
| IR CODE 160 TOGGLE 1 | LATE NIGHT MODE ON |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0019 125C | |
| IR CODE 161 TOGGLE 0 | LATE NIGHT MODE OFF |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0019 0032 1275 | |
| IR CODE 161 TOGGLE 1 | LATE NIGHT MODE OFF |
| 0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0031 0019 0019 0019 0019 0019 0032 1275 | |
| IR CODE 167 TOGGLE 0 | PREVIOUS DSP MODE |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0031 0019 0019 0032 0019 0019 0019 0019 1275 | |
| IR CODE 167 TOGGLE 1 | PREVIOUS DSP MODE |
| 0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0031 0019 0019 0032 0019 0019 0019 0019 1275 | |
| IR CODE 185 TOGGLE 0 | CONFIGURATION 1 |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0019 0019 0019 0019 0032 0019 0019 0032 1275 | |
| IR CODE 185 TOGGLE 1 | CONFIGURATION 1 |
| 0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0019 0019 0019 0019 0032 0019 0019 0032 1275 | |

SIGMA SSP HEX CODES

| IR CODE 186 TOGGLE 0 | CONFIGURATION 2 |
|---|-----------------|
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0019 0019 0019 0019 0032 0032 0031 0019 125C | |
| IR CODE 186 TOGGLE 1 | CONFIGURATION 2 |
| 0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0019 0019 0019 0019 0032 0032 0031 0019 125C | |
| IR CODE 187 TOGGLE 0 | CONFIGURATION 3 |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0019 0019 0019 0019 0032 0032 0019 0019 1275 | |
| IR CODE 187 TOGGLE 1 | CONFIGURATION 3 |
| 0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0019 0019 0019 0019 0032 0032 0019 0019 1275 | |
| IR CODE 188 TOGGLE 0 | CONFIGURATION 4 |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 125C | |
| IR CODE 188 TOGGLE 1 | CONFIGURATION 4 |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0019 0019 0019 0019 0019 0032 0019 0019 0019 125C | |
| IR CODE 189 TOGGLE 0 | CONFIGURATION 5 |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0019 0019 0019 0019 0019 0019 0032 0032 1275 | |
| IR CODE 189 TOGGLE 1 | CONFIGURATION 5 |
| 0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0019 0019 0019 0019 0019 0032 0032 1275 | |
| IR CODE 190 TOGGLE 0 | CONFIGURATION 6 |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0019 0019 0019 0019 0019 0019 0019 0032 0019 125C | |

SIGMA SSP HEX CODES

| IR CODE 190 TOGGLE 1 | CONFIGURATION 6 |
|--|---------------------|
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0031 0032 0019 0019 0019 0019 0019 0019 0019 0032 0019 125C | |
| IR CODE 206 TOGGLE 0 | NEXT CONFIGURATION |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0019 0019 0032 0019 0019 0019 0019 0032 0019 125C | |
| IR CODE 206 TOGGLE 1 | NEXT CONFIGURATION |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0019 0019 0032 0019 0019 0019 0019 0032 0019 125C | |
| IR CODE 207 TOGGLE 0 | LAST CONFIGURATION |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0019 0019 0032 0019 0019 0019 0019 0032 0019 1275 | |
| IR CODE 207 TOGGLE 1 | LAST CONFIGURATION |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0019 0019 0032 0019 0019 0019 0019 0032 0019 1275 | |
| IR CODE 216 TOGGLE 0 | DOLBY VOLUME TOGGLE |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0032 0019 0019 0032 0019 0019 0019 0019 0032 0019 125C | |
| IR CODE 216 TOGGLE 1 | DOLBY VOLUME TOGGLE |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0032 0019 0019 0032 0019 0019 0019 0019 0032 0019 125C | |
| IR CODE 217 TOGGLE 0 | LIPSYNC MENU |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0032 0019 0019 0032 0019 0019 0032 0019 0032 1275 | |
| IR CODE 217 TOGGLE 1 | LIPSYNC MENU |
| 0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0032 0019 0019 0032 0019 0019 0032 1275 | |

SIGMA SSP HEX CODES

| IR CODE 220 TOGGLE 0 | MODE 1: MONO |
|--|--------------------|
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0032 0019 0019 0019 0019 0032 0019 0019 0019 125C | |
| IR CODE 220 TOGGLE 1 | MODE 1: MONO |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0032 0019 0019 0019 0019 0032 0019 0019 0019 125C | |
| IR CODE 221 TOGGLE 0 | MODE 2: STEREO |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0032 0019 0019 0019 0019 0032 0019 0019 0019 0032 1275 | |
| IR CODE 221 TOGGLE 1 | MODE 2: STEREO |
| 0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0032 0019 0019 0019 0019 0032 0032 1275 | |
| IR CODE 222 TOGGLE 0 | MODE 3: PARTY |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0032 0019 0019 0019 0019 0019 0019 0019 0019 125C | |
| IR CODE 222 TOGGLE 1 | MODE 3: PARTY |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0032 0019 0019 0019 0019 0032 0019 0019 0019 0032 125C | |
| IR CODE 223 TOGGLE 0 | MODE 4: MONO PLUS |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0032 0019 0019 0019 0019 0019 0019 0019 0019 1275 | |
| IR CODE 223 TOGGLE 1 | MODE 4: MONO PLUS |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0032 0032 0019 0019 0019 0019 0019 0019 0019 0019 1275 | |
| IR CODE 224 TOGGLE 0 | MODE 5: MOVIE PLUS |
| 0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 0019 0019 125C | |

SIGMA SSP HEX CODES

| | |
|---|--|
| IR CODE 224 TOGGLE 1 | MODE 5: MOVIE PLUS |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 0019 125C | |
| IR CODE 225 TOGGLE 0 | MODE 6: MUSIC PLUS |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0019 0032 1275 | |
| IR CODE 225 TOGGLE 1 | MODE 6: MUSIC PLUS |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 0032 1275 | |
| IR CODE 226 TOGGLE 0 | MODE 7: DOLBY PRO LOGIC II |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0019 0032 0019 0019 0019 0019 0032 0031 0019 125C | |
| IR CODE 226 TOGGLE 1 | MODE 7: DOLBY PRO LOGIC II |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0019 0032 0019 0019 0019 0019 0032 0031 0019 125C | |
| IR CODE 227 TOGGLE 0 | MODE 8: DOLBY PRO LOGIC IIz MUSIC |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0019 0032 0019 0019 0019 0019 0032 0019 0019 1275 | |
| IR CODE 227 TOGGLE 1 | MODE 8: DOLBY PRO LOGIC IIz MUSIC |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0019 0032 0019 0019 0019 0019 0032 0019 0019 1275 | |
| IR CODE 228 TOGGLE 0 | MODE 9: DOLBY PRO LOGIC IIz MOVIE |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 125C | |
| IR CODE 228 TOGGLE 1 | MODE 9: DOLBY PRO LOGIC IIz MOVIE |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 125C | |

SIGMA SSP HEX CODES

| IR CODE 229 TOGGLE 0 | MODE 10: DOLBY PRO LOGIC IIz MATRIX |
|--|-------------------------------------|
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0031 0019 0019 0032 0019 0019 0019 0032 0019 0019 0032 0031 0032 1275 | |
| IR CODE 229 TOGGLE 1 | MODE 10: DOLBY PRO LOGIC IIz MATRIX |
| 0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0032 0019 0019 0032 0031 0032 1275 | |
| IR CODE 230 TOGGLE 0 | MODE 11: DOLBY PRO LOGIC IIz GAME |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0032 0019 0019 0032 0019 0019 0032 0019 125C | |
| IR CODE 230 TOGGLE 1 | MODE 11: DOLBY PRO LOGIC IIz GAME |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0032 0019 0019 0032 0019 0019 0032 0019 125C | |
| IR CODE 231 TOGGLE 0 | MODE 12: DTS NEO:6 |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0032 0019 0019 0032 0019 0019 0032 0019 1275 | |
| IR CODE 231 TOGGLE 1 | MODE 12: DTS NEO:6 |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0032 0019 0019 0032 0019 0019 0032 0019 1275 | |
| IR CODE 232 TOGGLE 0 | MODE 13: DTS NEO:6 MUSIC |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0019 0032 0019 125C | |
| IR CODE 232 TOGGLE 1 | MODE 13: DTS NEO:6 MUSIC |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0019 0032 0019 125C | |
| IR CODE 233 TOGGLE 0 | MODE 14: DTS NEO:6 CINEMA |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 1275 | |

SIGMA SSP HEX CODES

| | |
|---|-------------------------------------|
| IR CODE 233 TOGGLE 1 | MODE 14: DTS NEO:6 CINEMA |
| 0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 1275 | |
| IR CODE 234 TOGGLE 0 | MODE 15: DISCRETE |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0019 0032 0032 0031 0032 0031 0019 125C | |
| IR CODE 234 TOGGLE 1 | MODE 15: DISCRETE |
| 0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0019 0032 0032 0031 0032 0031 0019 125C | |
| IR CODE 235 TOGGLE 0 | MODE 16: DOLBY EX |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0019 0032 0032 0031 0032 0019 0019 1275 | |
| IR CODE 235 TOGGLE 1 | MODE 16: DOLBY EX |
| 0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0019 0032 0032 0031 0032 0019 0019 1275 | |
| IR CODE 236 TOGGLE 0 | MODE 17: DTS NEO:6 MUSIC ES |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0032 0019 0019 125C | |
| IR CODE 236 TOGGLE 1 | MODE 17: DTS NEO:6 MUSIC ES |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0032 0019 0019 0019 125C | |
| IR CODE 237 TOGGLE 0 | MODE 18: DTS NEO:6 CINEMA ES |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0032 0032 1275 | |
| IR CODE 237 TOGGLE 1 | MODE 18: DTS NEO:6 CINEMA ES |
| 0000 004A 0000 0010 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0019 0032 0032 0019 0019 0032 0032 1275 | |

SIGMA SSP HEX CODES

| IR CODE 247 TOGGLE 0 | EQ MENU |
|--|---------|
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 0032 0019 0032 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0019 0019 0032 0032 0019 0019 0019 1275 | |
| IR CODE 247 TOGGLE 1 | EQ MENU |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 004A 0032 0019 0019 0019 0019 0032 0032 0031 0019 0019 0032 0019 0019 0019 0019 0019 0032 0032 0019 0019 0019 0019 1275 | |

RC6 MODE 0, SYSTEM CODE 200

| IR CODE 13 TOGGLE 0 | MUTE TOGGLE |
|--|-------------|
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0032 0032 1275 | |
| IR CODE 13 TOGGLE 1 | MUTE TOGGLE |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0032 0032 1275 | |
| IR CODE 16 TOGGLE 0 | VOLUME UP |
| 0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 125C | |
| IR CODE 16 TOGGLE 1 | VOLUME UP |
| 0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 125C | |
| IR CODE 17 TOGGLE 0 | VOLUME DOWN |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 1275 | |
| IR CODE 17 TOGGLE 1 | VOLUME DOWN |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 1275 | |

SIGMA SSP HEX CODES

| IR CODE 56 TOGGLE 0 | F1 |
|--|----|
| 0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 125C | |
| IR CODE 56 TOGGLE 1 | F1 |
| 0000 004A 0000 0013 0095 0032 0019 0032 0019 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0032 0019 0019 0019 0019 0019 125C | |
| IR CODE 57 TOGGLE 0 | F2 |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0032 0019 0019 0032 1275 | |
| IR CODE 57 TOGGLE 1 | F2 |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 0032 0019 0019 0032 1275 | |
| IR CODE 134 TOGGLE 0 | F3 |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0032 0019 0019 0032 0019 125C | |
| IR CODE 134 TOGGLE 1 | F3 |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0032 0019 0019 0032 0019 125C | |
| IR CODE 135 TOGGLE 0 | F4 |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 1275 | |
| IR CODE 135 TOGGLE 1 | F4 |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 0032 0019 0019 0019 0019 1275 | |
| IR CODE 136 TOGGLE 0 | F5 |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 0019 0019 125C | |

SIGMA SSP HEX CODES

| IR CODE 136 TOGGLE 1 | F5 |
|--|------|
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0032 0031 0019 0019 0019 0019 125C | |
| IR CODE 137 TOGGLE 0 | F6 |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 0032 0031 0019 0019 0032 1275 | |
| IR CODE 137 TOGGLE 1 | F6 |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0032 0031 0019 0019 0019 0032 0031 0019 0019 0032 1275 | |
| IR CODE 138 TOGGLE 0 | F7 |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 0032 0031 0032 0031 0019 125C | |
| IR CODE 138 TOGGLE 1 | F7 |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0032 0031 0019 0019 0019 0032 0031 0032 0031 0019 125C | |
| IR CODE 139 TOGGLE 0 | F8 |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0019 0032 0031 0032 0019 0019 1275 | |
| IR CODE 139 TOGGLE 1 | F8 |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0032 0031 0019 0019 0019 0032 0031 0032 0019 0019 1275 | |
| IR CODE 152 TOGGLE 0 | MUTE |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0032 0019 0019 0032 0019 0019 0019 125C | |
| IR CODE 152 TOGGLE 1 | MUTE |
| 0000 004A 0000 0012 0095 0032 0019 0032 0019 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0032 0031 0019 0019 0032 0019 0019 0032 0019 0019 0019 125C | |

SIGMA SSP HEX CODES

| IR CODE 153 TOGGLE 0 | UNMUTE |
|---|--------|
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 0019 0032 004B 0018 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0032 0019 0019 0032 0019 0019 0032 1275 | |
| R CODE 153 TOGGLE 1 | UNMUTE |
| 0000 004A 0000 0011 0095 0032 0019 0032 0019 0019 0019 0019 004B 0031 0019 0019 0019 0032 0019 0019 0032 0031 0019 0019 0019 0019 0032 0031 0019 0019 0032 0019 0019 0032 0019 0019 0032 1275 | |